

## DATASHEET

# Cochlear™ Wireless Mini Microphone 2



The Cochlear™ Wireless Mini Microphone 2 transmits speech directly to Nucleus™ and Baha® sound processors from a range of up to 82 feet.\*

### Features:

- Small and lightweight
- One-to-one speech streaming with directional microphones
- Easy to use
- 82 foot range with clear line of sight

The Mini Microphone 2 optimizes signal-to-noise ratio in one-to-one communication. It sends the speaker's voice directly to the recipient's sound processors without the need for any extra devices. The Mini Microphone 2 is reliable and improves speech understanding in difficult listening situations where distance, background noise or poor acoustics are an issue. This may help to allow the listener to perform dual attention tasks that people with normal hearing may take for granted.

In essence the microphone is designed to extend the hearing range of the sound processor in a variety of situations, such as:

- at home
- in the car
- while dining out
- while traveling
- in place of worship
- in school, at a lecture

### Easy to connect

- Just press the pairing button on the Mini Microphone 2 and turn on the sound processor within 20 seconds and it automatically pairs with the sound processor.
- Pairing with a Cochlear™ Baha® Sound Processor can also be done through the fitting software.
- Once paired the microphone will stay paired with the sound processor.

### Easy to use

- Simply turn the microphone on and switch the sound processor into streaming mode.
- Easy to recharge using the included charger.
- Battery life: Typically 10 hours.
- Can be clipped onto clothing or worn with a lanyard.
- Volume control buttons for easy adjustment (incl. volume control lock) and mute button.
- Drop detector – mutes transmitted signal momentarily when dropped from heights above 30 inches.

### Volume setting range

The Mini Microphone has a total volume range from -24 dB to +12 dB in 3 dB increments (12 incremental steps total). The default setting is 0 dB, meaning the sound signal is transmitted to the processors without any additional amplification.

### 2.4 GHz wireless technology

- A smart, robust and reliable standard with a strong, clear and stable signal.
- No need to wear an intermediary device, as the signal is transmitted directly to the sound processor.


\*Clear line of sight

## Description

Article numbers:

P770844 Cochlear Wireless Mini Microphone 2 US

1. ON/OFF button
2. Microphones
3. Status indicator light (LED)
4. Micro USB for charging
5. Pairing button
6. Mounting clip
7. Volume down
8. Mute button
9. Volume up
10. Mute indicator light (LED)



## Technical information

Dimensions	L 2 x H 1 x W 0.8" / L 53 x H 25.5 x W 20.3 mm
Weight	0.60 oz / 17 grams
Power supply	Built-in rechargeable battery
Battery life (fully charged)	Typically 10 hours
Power connection	Micro USB
Charging time	Max 3 hours, depending on initial state of the battery
Wireless connections	Multiple sound processors per Mini Microphone. Up to 3 streaming devices (combination of Mini Microphones and TV Streamers) per binaural set of sound processors.
Streaming range	82 feet (Clear line of sight)
Streaming latency	20 ms
Audio interface	Dual microphone voice pick-up
Audio Frequency range	100-8000 Hz $\pm$ 3 dB
Microphone acoustic sensitivity	Equal to sound processor $\pm$ 3 dB
Clip (Mini Microphone in vertical position)	Noise suppression microphone mode with directional focus towards speaker's mouth
Microphone limiter	Acoustic inputs above 85 dB SPL are limited to avoid unpleasantly loud outputs
ESD tolerance	According to IEC 61000-4-2 Electro-static discharge immunity test standard. 6kV Contact discharge method / 8kV Air discharge method
Wireless frequency	2.4 GHz
Hearing Instrument Wireless Interface Compliance	EN300 328, ETSI EN 300 440-1 FCC CFR 47 Part 15, Subpart C, § 15.247
Operating & charging temperature	0 to 45 °C / 32 to 113 °F May also be used in environments below 32° F with reduced battery lifetime
Storage temperature	-4 to 113 °F / -20 to 45 °C

All data is subject to change. Read instructions for use.

[www.Cochlear.com/US](http://www.Cochlear.com/US)

Follow us on   

**Cochlear Americas**  
13059 East Peakview Avenue  
Centennial, CO 80111 USA  
Telephone: 1 303 790 9010  
Concierge: 1 866 922 9211

**Cochlear Canada Inc.**  
2500-120 Adelaide Street West  
Toronto, ON M5H 1T1 Canada  
Telephone: 1 416 972 5082  
Fax: 1 416 972 5083

Cochlear Wireless Accessories are compatible with select Cochlear sound processors.

See [www.Cochlear.com](http://www.Cochlear.com) for full compatibility details.

©2016 Cochlear Limited. All rights reserved. Hear now. And always and other trademarks and registered trademarks are the property of Cochlear Limited. The names of actual companies and products mentioned herein may be the trademarks of their respective owners.

 FUN2603 ISS1 MAR16

Hear now. And always

  
**Cochlear®**